

Reihe 10

Informatik/
Kommunikation

Nr. 850

Yuhong Song, M. Sc.,
Yichang / China

Suppressing Electro- magnetic Interference in Switching Converters by Chaotic Duty Modulation



FernUniversität in Hagen
**Schriften zur Informations-
und Kommunikationstechnik**

Suppressing Electromagnetic Interference in Switching Converters by Chaotic Duty Modulation

DISSERTATION

zur Erlangung des akademischen Grades

DOKTOR-INGENIEURIN

der Fakultät für Mathematik und Informatik
der FernUniversität in Hagen

von

Yuhong Song, M.Sc.

Yichang/China

Hagen, 2016

Fortschritt-Berichte VDI

Reihe 10

Informatik/
Kommunikation

Yuhong Song, M. Sc.,
Yichang / China

Nr. 850

Suppressing Electro-
magnetic Interference in
Switching Converters by
Chaotic Duty Modulation



FernUniversität in Hagen
Schriften zur Informations-
und Kommunikationstechnik

Song, Yuhong

Suppressing Electromagnetic Interference in Switching Converters by Chaotic Duty Modulation

Fortschr.-Ber. VDI Reihe 10 Nr. 850. Düsseldorf: VDI Verlag 2017.

104 Seiten, 64 Bilder, 18 Tabellen.

ISBN 978-3-18-385010-5, ISSN 0178-9627,

€ 43,00/VDI-Mitgliederpreis € 38,70.

Keywords: Switching power supply – Switching converter – Chaotic duty modulation – Electromagnetic interference (EMI) – Electromagnetic compatibility (EMC) – Stability – Remaining useful life

Abstract: The switching converter generates serious electromagnetic interference (EMI), which impairs other devices' performance and harms human being's health. As a way of chaos technique, chaotic modulation has been developed to suppress EMI of the switching converter by dispersing the energy into a wide frequency band and smoothing the peaks of the EMI spectrum. Unlike the well-studied chaotic frequency modulation, the chaotic duty modulation is concerned in this dissertation, which is just to change the duty of the transistor driving-pulse while maintains the fixed switching frequency. Chaotic duty modulation is realized by appending an external chaotic signal to the existing PWM module of the switching converter, which is practicable without the loss of the generality. It is thus verified that this proposal of using chaotic duty modulation in switching converters for EMI suppression is feasible and lays a foundation for industrial applications.

Bibliographische Information der Deutschen Bibliothek

Die Deutsche Bibliothek verzeichnet diese Publikation in der Deutschen Nationalbibliographie; detaillierte bibliographische Daten sind im Internet unter <http://dnb.ddb.de> abrufbar.

Bibliographic information published by the Deutsche Bibliothek

(German National Library)

The Deutsche Bibliothek lists this publication in the Deutsche Nationalbibliographie (German National Bibliography); detailed bibliographic data is available via Internet at <http://dnb.ddb.de>.

Schriften zur Informations- und Kommunikationstechnik

Herausgeber:

Wolfgang A. Halang, Lehrstuhl für Informationstechnik

Herwig Unger, Lehrstuhl für Kommunikationstechnik

FernUniversität in Hagen

© VDI Verlag GmbH · Düsseldorf 2017

Alle Rechte, auch das des auszugsweisen Nachdruckes, der auszugsweisen oder vollständigen Wiedergabe (Fotokopie, Mikrokopie), der Speicherung in Datenverarbeitungsanlagen, im Internet und das der Übersetzung, vorbehalten.

Als Manuskript gedruckt. Printed in Germany.

ISSN 0178-9627

ISBN 978-3-18-385010-5

Acknowledgements

My former colleague at the Shunde Polytechnic, Dr. Ping Li, introduced me to Prof. Wolfgang A. Halang in 2010 as he visited our laboratory. Wonderfully, the casual meeting has greatly changed my life, just like “butterfly effect” in the chaos theory, which has been used in my research work for my Ph.D degree. In the following year, I was invited to work for a project funded by German Industry Association, meanwhile, to pursue my Ph.D degree at the FernUniversität in Hagen.

Before 2010, I only knew that “butterfly effect” relates to one sentence, “A butterfly from the Amazon river basin rainforest in South America, occasionally flaps its wings, which could cause a tornado in Texas of the United States two weeks later”. With the further study, I understood the real meaning behind “butterfly effect”, which is the poetic description of the chaotic phenomenon. Together with relativity and quantum mechanics, chaos is considered as one of the three monumental scientific discoveries in the twentieth century. Our real world is essentially nonlinear, thus chaos is ubiquitous, attracting so much research interest in the past few decades. However, for a long time, chaos has been considered to be harmful and useless, and thus controlled to prevent its appearance in the nonlinear systems. Recently, chaos has been found helpful and useful for some engineering applications, such as secure communication, motor control and electromagnetic interference (EMI) suppression. However, the research achievements are mostly embodied in the theory and laboratory prototype and industrial applications have been in a wait-and-see status.

The idea of trying to offer the feasible schemes for commercial switching converters motivated me to make a research on applying chaos in reducing EMI. Chaos technique has been applied in switching converters in two ways: parameter control and spread spectrum modulation. The parameter control is strictly demanded to maintain chaos under various conditions, i.e., different loads, which results in the complexity of system design. Chaotic modulation has been developed to suppress EMI of switching converters by dispersing the energy into a wide frequency band and smoothing the peaks of the EMI spectrum. My research, focusing on chaotic duty modulation, has proposed the spread spectrum schemes in commercial switching converters. Meanwhile, simulations and experiments have been conducted to verify the effectiveness of the proposed schemes on EMI reduction. Furthermore, on the basis of spectral properties of chaotic signal, which is normally represented by Fourier Transform, the central frequency has been defined to be the frequency corresponding to the greatest spectral peak of chaotic signal. It has been proved that the chaotic duty modulation is the most effective to suppress EMI when the central frequency of chaotic signal is equal to the switching frequency of transistor in switching converters.

This thesis bears painstaking efforts of many persons. First of all, I would like to express my sincere gratitude to my supervisor Prof. Zhong Li for his guidance with patience. Without his keen insight and constant encouragement, my thesis would not have appeared in the present form. I would also thank his wife, Mrs. Juan Mei, for her concern to my

daily life. Further, I would like to thank my co-advisor Prof. Wolfgang A. Halang for his continuous support and kindly help in both my work and daily life, and thank his wife, Mrs. Halang, for her kindness.

Special thanks go to my colleagues Mrs. Junying Niu and Dr. Guidong Zhang for their great co-operation, fruitful discussion, encouragement and care through the whole course of my Ph.D study. I would also thank Mrs. Jutta Doring and Mr. Schubert for their technical support at the FernUniversität in Hagen, Germany. I am very grateful to Prof. Holger Hirsch for his support to carry out my experiment at University of Duisburg-Essen, Germany. My appreciation goes to Dr. Wenping Xiao, Dr. Yajun Li and Dr. Fan Xie for giving me a lot of suggestions about my thesis. I owe my thanks to Dr. Ping Li for her recommendation and also thank my German friends Mr. and Mrs. Dannert, Mr. and Mrs. Fisher for their kindness.

Cordial thanks also go to my family for the love and concern all the time, to my parents and mother-in-law for their consideration, to my husband for his understanding and support, and to my son, who is a sunny boy and encourages me to engage in the scientific research. In addition, my greatest gratitude goes to my sister Dr. Yinhong Song for her encouragement and help.

Sincere thanks go to the Shunde Polytechnic, whose policy of training personnel benefits my scientific research and Ph.D study in Germany.

Contents

Abstract	VII
1 Introduction	1
1.1 Switching Converters	1
1.2 EMI and EMC	2
1.2.1 EMI Elements	2
1.2.2 EMC Test	2
1.2.3 Visualization of EMI	3
1.3 EMI Suppression in Switching Converters	6
1.3.1 Filtering and Shielding	6
1.3.2 Soft Switching	7
1.3.3 Chaos Technique	7
1.3.4 Effect of Chaotic Signal on Modulation	10
1.4 Motivation	10
1.5 About the Dissertation	11
2 Circuitry Design for Chaotic Modulation	14
2.1 Introduction	14
2.2 Chaotic Frequency Modulation	14
2.2.1 Principle of Spectrum Spreading	14
2.2.2 Circuitry Design	16
2.3 Chaotic Duty Modulation	17
2.3.1 Principle of Spectrum Spreading	17
2.3.2 Circuitry Design	19
2.4 Simulations	20
2.5 Summary	21
3 Central Frequency of Chaotic Signals	23
3.1 Introduction	23
3.2 Duffing Oscillator	23
3.3 Chua's Circuit	25
3.3.1 Unitary Processing	26
3.3.2 The Oscillating Frequency	26
3.4 Central Frequency	27
3.5 Summary	29
4 Effect of Central Frequency on EMI Reduction	30
4.1 Introduction	30
4.2 Frequency Spectrum under Chaotic modulation	31
4.2.1 Chaotic Duty Modulation	31
4.2.2 Spectral Analysis	32
4.3 Chaotic Analogue Signal	34
4.3.1 Parameter Configuration for Central Frequency	34
4.3.2 Simulations and Experiments	34
4.4 Chaotic Digital Signal	37
4.4.1 Chaotic Maps	37
4.4.2 Algorithm Design	37
4.4.3 Simulations and Experiments	39
4.5 Summary	41

5	Realizing Chaotic Duty Modulation	44
5.1	Introduction	44
5.2	Implementation of Chaotic Duty Modulation	44
5.3	Analogue Chaotic Duty Modulation	45
5.3.1	System and TL494	45
5.3.2	Design of Chaotic Signal Generator	47
5.3.3	Simulations and Experiments	48
5.4	Digital Chaotic Duty Modulation	52
5.4.1	Scheme Design	52
5.4.2	EMC Test	53
5.5	Summary	54
6	System Stability under Chaotic Duty Modulation	57
6.1	Introduction	57
6.2	Circuit Average Model of a Half-Bridge Converter	57
6.2.1	Circuit Description	57
6.2.2	Large Signal Model	60
6.2.3	Direct Current Model and Small Signal Model	66
6.3	Stability	68
6.4	Summary	71
7	The Remaining Useful Life under Chaotic Modulation	72
7.1	Introduction	72
7.2	Failure Model of Critical Components	73
7.3	Impact of Chaotic Modulation on Critical Components	76
7.3.1	Electrolytic Capacitor	76
7.3.2	Power Switch	77
7.4	Failure Influence of Chaotic Modulation	78
7.4.1	Parameters of Analogue Signal Generator	78
7.4.2	Operation Precision of Digital Signal Generator	78
7.4.3	Simulations	78
7.5	Summary	81
8	Tests of Input and Output Characteristics	83
8.1	Introduction	83
8.2	Input Characteristics	83
8.3	Output Characteristics	84
8.3.1	Voltage Accuracy	84
8.3.2	Output Transient Response	85
8.4	Comparisons of Test Results	85
8.5	Summary	87
9	Conclusions	88
	References	90

Abstract

A switching power supply, namely switching converter, which is characterized by high efficiency, small volume and light weight, has developed rapidly in recent years and has been gradually deployed instead of linear power supplies in electronic and electrical domains. The switching power supply makes use of the pulse-width modulation (PWM) technology to control the nonlinear components, so that they have a switching action of high frequency, resulting in high change rates of voltage and current. Consequently, the switching converter generates serious electromagnetic interference (EMI), which impairs other devices' performance and harms human being's health. Hence, suppressing EMI has become a common concern in the design and the application of switching converters.

Traditionally, EMI is dealt by filtering or shielding, or both. Filtering aims to reduce the conducted EMI by adding the filters to the system. In practice, multiple filters should be employed in a switching converter because a single filter is restricted by its narrow frequency band. Shielding aims to block the converter from emitting or receiving the radiated EMI with barriers made of conductive material. These traditional filtering and shielding techniques have the disadvantages in weight, size and cost, and their engineering applications depend on the experience of engineers. Additionally, it has been found that soft switching technique can be used to reduce EMI. However, it needs an auxiliary control module to guarantee zero voltage or zero current during the transformational period of transistors, resulting in a complicated design. Hence, using chaos in switching converters has become new preferable technique to tackle the EMI problems due to the pseudo-random and continuous spectrum characteristics of chaos.

As a way of chaos technique, chaotic modulation has been developed to suppress EMI of the switching converter by dispersing the energy into a wide frequency band and smoothing the peaks of the EMI spectrum. It is well known that the effectiveness of EMI suppression is related to chaotic signals used for chaotic modulation. From this study, it is further found that the central frequency of a chaotic signal, corresponding to the largest peak of its frequency spectrum, should be close to a half of the switching frequency of a power supply to reach optimal EMI suppression.

Unlike the well-studied chaotic frequency modulation, the chaotic duty modulation is concerned in this dissertation, which is just to change the duty of the transistor driving-pulse while maintains the fixed switching frequency. Chaotic duty modulation is realized by appending an external chaotic signal to the existing PWM module of the switching converter, which is practicable without the loss of the generality.

It is followed with a qualitative verification of the stability of power supplies under chaotic duty modulation via the classic control theory, and practically, the useful life through the failure model and critical components, which is also ensured under chaotic duty modulation. It is thus verified that this proposal of using chaotic duty modulation in switching converters for EMI suppression is feasible and lays a foundation for industrial applications.

Key Words: Switching power supply, Switching converter, Chaotic duty modulation, Electromagnetic interference (EMI), Electromagnetic compatibility (EMC), Stability, Remaining useful life